

# TaHoma<sup>®</sup>

## Tahoma box (v2)



Connected Home (Tahoma Box)	
<b>Intuitive</b>	Convenient interface to centralize & control the equipment of the house, even remotely
<b>Evolutive</b>	Compatible with a wide range of equipment from Somfy and its partners
 <b>Agenda</b>	Manage your connected home to suit your lifestyle
 <b>Smart</b>	Automate devices depending on conditions (sensors, detectors, timer, etc.)
 <b>Scenarios</b>	Activating simultaneously several equipment by a single click.

Installation	
<b>1/ Connect TaHoma box to the Internet box/router (using the supplied RJ45 cable) and to the power supply (with the supplied cable)</b>	
<b>2/ Activate Tahoma on: <a href="http://www.somfy-connect.com">www.somfy-connect.com</a></b>	
<b>3/ Start using TaHoma by setting-up your Connected home</b>	
<b>=&gt; Use the Tahoma web interface or download the Tahoma mobile applications</b>	



Compatibility	
<b>Mobile applications</b>	iPhone            Android
<b>Web Browsers</b>	
<b>Protocols</b>	Protocole <b>Honeywell</b> With Dongle            With Dongle            With Dongle
<b>Partners</b>	 

# Tahoma<sup>®</sup>

## Tahoma box (v2)



### Technical Specifications

Element	Tahoma
<b>Protocols/Frequency</b> <i>Frequency bands and Maximum power used</i>	<ul style="list-style-type: none"> <li>io - 2 ways (868-870 MHz)  <i>io-homecontrol<sup>®</sup> tri-band two-way, with LBT (Listen Before Talk)</i>            868.000 MHz - 868.600 MHz - ERP &lt;25 mW            868.700 MHz - 869.200 MHz - ERP &lt;25 mW            869.700 MHz - 870.000 MHz - ERP &lt;25 mW</li> <li>RTS (433Mhz)            433.050 MHz - 434.790 MHz - ERP &lt;10 mW</li> </ul>
<b>Dimensions (lxPxxh)</b>	110 x 71,25 x 28,13 mm
<b>Weight</b>	≈ 235gr
<b>Power</b>	μUSB 5VDC / 500mA Power supply 110/230V- 50/60 Hz (E/F/J Type compliant)
<b>Consumption</b>	0,1 A (nominal)
<b>Connectors</b>	1x Ethernet RJ45 1x Micro-USB 1x USB port
<b>Operating ambient temperature</b>	+0°C to +50°C / IP 20
<b>Color</b>	White
<b>Others</b>	LED (Red/Green/Orange/White) "Reset" button
<b>In the box</b>	1x USB power adapter 1x RJ45 cable 1m 2x Quick start guides 1x Legal notice



# Tahoma<sup>®</sup>

## Tahoma box (v2)



Functional Specifications	
Max equipments (all protocols) : 200*	
Equipments	Max
IO equipments	200
RTS equipments	50
RTD equipments	50
RTDS equipments	50
Ramses equipments	3 Evotouch
EnOcean equipments	128
OVP equipments	200
Caméras equipments	5
Zwave equipments	232
Scénario player equipments	20
HUE Bridge	1 (50 lamps)
Functions	Max
Scenario	40
Day	40
SMART	20
Others	Max
Condition in a SMART	6**
E-mail alerts	3**
SMS numbers alerts	3**
Push alerts	Unlimited

*\*More equipments it's possible but not guaranteed.*